

CLAIMS

What is claimed is:

1. A programmable system for transmitting an arbitrary M-ary modulated optical signal comprising:
 - a transmitter laser for providing a laser beam;
 - an amplitude modulator for amplitude modulating the laser beam;
 - 5 an optical fiber for coupling the laser beam to the amplitude modulator;
 - a phase modulator in series with the amplitude modulator for phase modulating the amplitude modulated laser beam;
 - an optical fiber coupled between the amplitude modulator and the phase modulator;
 - 10 constellation generating apparatus that is responsive to input data and a data modulator clock signal for generating a constellation of data points that are input into the amplitude and phase modulator to amplitude and phase modulate the laser beam; and
 - an electrical delay for synchronizing the arrival of the amplitude modulated light at the phase modulator with a signal from a phase angle portion of the constellation
 - 15 generating apparatus arriving at the phase modulator.
2. The system recited in Claim 1 wherein the electrical delay comprises a length of coaxial cable.
3. The system recited in Claim 1 wherein the amplitude portion of the constellation generating apparatus comprises amplitude symbol mapping logic that is responsive to input data and a data clock signal, weighting apparatus, summing apparatus, and amplifying apparatus.
4. The system recited in Claim 1 wherein the phase portion of the constellation generating apparatus comprises phase angle symbol mapping logic that is responsive to the input data and the data clock signal, weighting apparatus, summing apparatus, amplifying apparatus, and delaying apparatus.
5. The system recited in Claim 1 wherein the modulation format of the optical signal of an optical link is reconfigured to maximize data transmission for a varying allowed bit error rate and varying available link optical dynamic range.

6. The system recited in Claim 1 which predistorts the transmitted constellation to compensate for nonlinearity in the optical link.

7. The system recited in Claim 1 which predistorts the transmitted constellation to compensate for self-phase modulation.

8. The system recited in Claim 1 which compensates for performance variations in the components of a communication link.

9. An optical transmitting method comprising the steps of:
 outputting a laser beam;
 generating a constellation of data points in response to input data and a data clock signal that are used to amplitude and phase modulate the laser beam;
 5 amplitude modulating the laser beam using the constellation of data points;
 delaying the constellation of data points used for phase modulation to synchronize it with the amplitude modulated laser beam;
 phase modulating the amplitude modulated laser beam using the delayed constellation of data points to produce a modulated output beam.

10. The optical transmitting method recited in Claim 9 wherein the constellation of data points comprises a Grey code.

11. A programmable system for transmitting an arbitrary M-ary modulated optical signal comprising:
 an amplitude modulator for amplitude modulating an optical signal;
 a phase modulator for phase modulating the optical signal;
 5 a constellation generating apparatus for generating an amplitude control signal and a phase control signal from an input data signal, the amplitude control signal Input to the amplitude modulator and the phase control signal input to the phase modulator.
 together the amplitude control signal and the phase control signal representing a constellation of data points such that the amplitude and phase modulated optical signal
 10 is an arbitrary M-ary modulated optical signal.

12. The system according to claim 11, wherein the amplitude modulator modulates the optical signal before the phase modulator modulates the optical signal and the system further comprising a delay, the delay delaying the phase control signal to

5 synchronize the phase modulation of the optical signal with a delay between the
amplitude modulator and the phase modulator.

13. The system according to claim 11, wherein the phase modulator modulates
the optical signal before the amplitude modulator modulates the optical signal and the
system further comprising a delay, the delay delaying the amplitude control signal to
5 synchronize the amplitude modulation of the optical signal with a delay between the
phase modulator and the amplitude modulator.

14. The system according to claim 11, wherein an amplitude control signal
generating portion of the constellation generating apparatus includes an adaptable
amplitude symbol mapping logic.

15. The system according to claim 14, wherein the amplitude symbol mapping
logic has a plurality of outputs, the outputs being weighted and combined to form the
amplitude control signal.

16. The system according to claim 11, wherein a phase control signal generating
portion of the constellation generating apparatus includes an adaptable phase symbol
mapping logic.

17. The system according to claim 14, wherein the phase symbol mapping logic
has a plurality of outputs, the outputs being weighted and combined to form the phase
control signal.

18. The system according to claim 11, wherein the constellation generating
apparatus is reconfigured to generate respective amplitude control and phase control
signals to produce an optical signal for maximizing data transmission over present
optical link conditions.

19. The system according to claim 11, wherein the constellation generating
apparatus is reconfigured to generate respective amplitude control and phase control
signals to produce a predistorted optical signal.

20. The system according to claim 19, wherein the predistortion compensates
for one or more factors selected from nonlinearity in an optical link, self-phase
modulation and performance variations in components of a communications link.